

Instructions for Tuning your receiver to the Optus D2 Satellite

Healing HSS851

Before you begin identify the following buttons on the remote control for the satellite receiver:- **Menu, exit, OK, the up-down and left-right buttons, and the red, green, yellow and blue buttons.**

Switch on the satellite receiver and TV as you normally would to watch one of the channels:- now you are ready to begin:-

Note:- When you 'select' an item on the on-screen menu it will be a different colour to the other items

To scan in the channels:-

1. Press the **menu button** and select **Installation** with the **up or down** buttons and press **OK**
2. Select **Auto Scan** with the **up or down** buttons and press **OK**
3. Press the **Green** button so that it reads **Free** under **Scan Mode**
4. Press the **Yellow** button so that it reads **On** under **Blind Scan**
5. Press the **Blue** button so that it reads **Quick Search** under **Scan Type**
6. Press the **Red** button to commence the scan

It will take about ten minutes for the scan to be completed

To organize the channels:-

1. Press **menu**
2. Select **Channel Organizer** with the **up or down** buttons and press **OK**
3. Select **Channel Manager** with the **up or down** buttons and press **OK**
4. To move a channel highlight the **Move** column on the same row as the channel you wish to move
5. Press **OK** and use the **up or down** buttons to move the channel and press **OK**
6. Repeat steps 4-6 for each channel you want to move.
7. When completed press the **exit** button - wait while the data is saved
8. Press the **exit** button two times to close the on-screen menus

If you have another brand of satellite receiver, these are the new parameters for Optus D2 that will need to be entered in to your satellite receiver.

Freq 12,706 GHz
Symbol rate 22,500
Pol Vertical
FEC 3/4